

**POG / PIN-OUT**

<b>Parts Side</b>	<b>Pin</b>	<b>Solder Side</b>
Ground (Black)	1	Ground
Diag Key / Logic Door Gnd	2	Speaker Ground
+5 VDC	3	+5 VDC
+5 VDC (N/U)	4	+5 VDC (N/U)
+12 VDC	5	+12 VDC (N/U)
+12 VDC	6	+12 VDC
Key	7	Key
Counter "A" (In)	8	Counter "B" (Out)
Coin Lockout	9	Bill Lockout (Grey)
Speaker Out	10	N/U (RVST)
Hopper Drive Option	11	1340 RxD From B/A (Or/Wh)
Video Red	12	Video Green
Video Blue	13	Video Sync
Video Ground	14	Diagnostics Keyswitch
Counter "C" (Played)	15	Counter "D"
Coin Switch	16	Cash Door Switch
B/A Interrupt Line(Y/Wh)	17	Main Door Switch
Attendant Key Switch	18	Logic Door Switch
Hopper Tech	19	Tilt Input
N/U	20	Hopper Low Switch
N/U Ticket	21	Hopper Full Switch
Card Reader Input Option	22	Hopper Coin Out
Optional Play Switch	23	Call Attnd. Switch (Grn/Wh)
Hopper Drive Option	24	Diverter Coil
Bell	25	B/A Send Line
N/U	26	Counter "E"
CRD RDT Out/Counter "G"	27	Counter "F"
Optional Play Lamp	28	Call Attendant Lamp

<b>B/A for Mars</b>	<b>Notch Up</b>
Black	Yel/Wh Or/Wh
Grey	Green/Wh ---
120	--- 120